

Zeta Battery Operated Detectors

(ZT-ST5, ZT-ST5/10 & ZT-TH5)



Description

The ZT-ST5 & ZT-ST5/10 stand-alone photoelectric residential smoke alarms are NF approved and can be calibrated to either UL, BSI or VdS requirements.

They feature VdS and UL-approved photoelectric sensing components with precise smoke detection and long life operation (5 year life with a 3V lithium battery, 1450mh) or (10 years with a 3V long life lithium battery, 1600mh). A proved quality with 10 million pieces installed over the world. Russian standard model available too.

The ZT-TH5 stand-alone heat detector was designed with precise microprocessor control integrating both Rate-of-Rise and Fixed Temperature heat detection.

It's perfectly suitable for installation in all environments especially the kitchen, garage, factory etc. The ZT-TH5 uses a 9V alkaline battery and meets EN 54-5 standards.

Technical Specification

| Model | ZT-ST5 | ZT-ST5/10 | ZT-TH5 |
|-------------------|---|------------------------------|----------------------|
| Part Number | 47-037-5 | 47-037-10 | 47-035 |
| Smoke Sensitivity | (2.31 ± 1.37)% / ft Obscuration (UL standard) 0.010 dB/m to 0.160 dB/m (VdS EN 14604) | | |
| Power supply | 3V lithium battery | 3V long life lithium battery | 9V alkaline battery |
| Battery life | 5 Year | 10 Years | 1 Year |
| Low battery life | Up to 30 days warning signal | | |
| Alarm indicator | Continuously emitting red light | | Red LED Flashing |
| Alarm sound level | 85dB at 3m | | Exceeding 85dB at 3m |
| Operating Temp. | 0°C to 50°C | | |
| Humidity | 10% to 95%RH, no condensation or icing | | |
| Interconnection | Up to 38 units | | |

Features

- ✓ Photoelectric sensing technology (ZT-ST5 & ZT-ST5/10)
- ✓ Electronic thermistor sensing technology (ZT-TH5)
- ✓ Easy installation and maintenance.
- ✓ Sealed Battery case of the back available (with 10-year Li Battery model)
- ✓ Sleek low-profile design
- ✓ SMD circuit board design - quality and reliability guaranteed
- ✓ Low-battery warning
- ✓ Test button verifies battery and alarm operation
- ✓ Loud alarm signal of exceeding 85 dB in alarm mode
- ✓ Five-year limited warranty
- ✓ HUSH button, to stop the alarm from sounding
- ✓ 10-year Long-life lithium battery (ZT-ST5/10 only)
- ✓ The power supply will be cut out automatically when removing the detector from the base